

Comment on “Noise in the helical edge channel anisotropically coupled to a local spin”

(Pis'ma v ZhETF 108, 700 (2018))

I. S. Burmistrov⁺¹⁾, P. D. Kurilovich*, V. D. Kurilovich*

⁺L. D. Landau Institute for Theoretical Physics Russian Academy of Sciences, 119334 Moscow, Russia

*Department of Physics, Yale University, New Haven, CT 06520, USA

Submitted 12 March 2019
Resubmitted 12 March 2019
Accepted 21 March 2019

DOI: 10.1134/S0370274X19090145

In [1] the current noise in the helical edge channel anisotropically coupled to a local spin 1/2 has been computed. In addition to the noise, a result for the backscattering current I_{bs} was reported. The latter formula (see Eq. (7) of [1]) does not coincide with the expression for I_{bs} derived in our recent work (see Eq. (22) of [2]) for a general form of the exchange interaction matrix. Below we shall argue that, in general, the result of [1] for the backscattering current is *erroneous*. Equation (7) of [1] gives the correct answer for the diagonal exchange matrix only. The incorrect result of [1] is a consequence of the assumption (which was also done in [3]) that the density matrix of the impurity spin, ρ_S , is diagonal in the eigenbasis of S_z (see Eq. (2) of [1]). As we demonstrated in [2], a careful analysis of the problem invalidates this assumption.

In order to set notations, we define the Hamiltonian describing the exchange interaction between the helical edge states and a magnetic impurity as $H_{int} = J_{jk} S_j s_k$, where \mathbf{S} (\mathbf{s}) denotes the operator of the impurity spin (the spin density of helical electrons) and J_{jk} is a 3×3 exchange matrix. In [1] the following form of the exchange matrix was considered

$$J = \begin{pmatrix} 2(J_0 + J_2) & 0 & 2J_a \\ 0 & 2(J_0 - J_2) & 0 \\ 2J_1 & 0 & J_z \end{pmatrix}. \quad (1)$$

We note that in our paper [2] we used dimensionless exchange matrix $\mathcal{J}_{jk} = \nu J_{jk}$. Here $\nu = 1/(2\pi v)$ stands for the density of states per edge mode and v denotes the velocity of the helical states.

To illustrate our point we first consider the case $J_2 = J_1 = 0$ and the regime $V \gg T$. Then, accord-

ing to Eq. (7) of [1] the backscattering current is given by ($G_0 = e^2/h$)

$$I_{bs}^{NRS} = -G_0 T J_a^2 / (2v^2). \quad (2)$$

This result should be contrasted with our result [2]:

$$I_{bs} = -G_0 \frac{V}{2v^2} \frac{2J_a^2 J_0^2}{2J_a^2 + J_z^2}. \quad (3)$$

In addition to a very different dependence of the backscattering current on the elements of the exchange matrix, Eq. (2) predicts saturation of the backscattering current at $V \gg T$ whereas Eq. (3) does not. This saturation occurs due to the full polarization of the magnetic impurity along z -axis by the applied voltage $V \gg T$. However, such a polarization is a consequence of an erroneous assumption that ρ_S is diagonal in the eigenbasis of S_z . In fact, there are no physical reasons for the full polarization (along z -axis) to occur: the magnetic impurity remains partially polarized in a direction tilted with respect to z -axis for arbitrary large voltage (see discussion around Eq. (26) in [2]).

To be more specific, the polarization along z -axis predicted by [1] follows from a claim that the dephasing of the impurity spin is mainly induced by the term $J_z S_z s_z$ in H_{int} . However, the term $2J_a S_x s_x$ enters H_{int} on the equal grounds and thus has to be taken into consideration to properly account for the dephasing. In particular, if $J_z = 0$ the magnetic impurity gets polarized along x -axis for $V \gg T$. In this regime, the backscattering is induced by the term $2J_0 (S_x s_x + S_y s_y)$ in the Hamiltonian and is insensitive to the precise value of J_a . This is consistent with our Eq. (3) and not consistent with Eq. (2).

¹⁾e-mail: burmi@itp.ac.ru.

Secondly, we consider the case $J_2 = J_a = 0$. Then, Eq. (7) of [1] predicts a linear in V backscattering current

$$I_{\text{bs}}^{\text{NRS}} = -G_0 \frac{V}{4v^2} J_1^2. \quad (4)$$

Our result for this case coincides with Eq. (4) in the regime $V \gg T$. This occurs because the density matrix of the magnetic impurity ρ_S is *indeed diagonal* in the eigenbasis of S_z for $J_a = 0$ and $V \gg T$.

In the regime of linear conductance ($V \ll \nu |J_{jk}| T$), our result for the backscattering current reads

$$I_{\text{bs}} = -G_0 \frac{V}{4v^2} \frac{J_1^2 (J_z^2 + 2J_1^2)}{J_z^2 + 2J_1^2 + 4J_0^2}. \quad (5)$$

The discrepancy between Eqs. (4) and (5) is due to the non-diagonal structure of ρ_S in the eigenbasis of S_z in the linear regime. As one can see, our result (5) trans-

forms into Eq. (4) provided $|J_z| \gg |J_{0,1}|$, i.e., precisely when ρ_S is diagonal in the eigenbasis of S_z .

To summarize, the result for the backscattering current reported in [1] is incorrect since its derivation relies on the erroneous assumption. This also questions the result of [1] for the current noise (for the correct result for the shot noise in the regime $V \gg T$ see [4]).

-
1. K. E. Nagaev, S. V. Remizov, and D. S. Shapiro, JETP Lett. **108**, 664 (2018); arXiv:1810.05831.
 2. P. D. Kurilovich, V. D. Kurilovich, I. S. Burmistrov, and M. Goldstein, Pis'ma v ZhETF **106**, 575 (2017) [JETP Lett. **106**, 593 (2017)].
 3. L. Kimme, B. Rosenow, and A. Brataas, Phys. Rev. B **93**, 081301 (2016).
 4. P. D. Kurilovich, V. D. Kurilovich, I. S. Burmistrov, Y. Gefen, and M. Goldstein, arXiv:1903.03965.